



2260d Translation Order Guide #1

Primary Directory Number Configuration – Tone Commander 2260d Console

1.	Customer Name:	
2.	Customer Contact:	
3.	Service Address:	
4.	Billing Telephone #:	
5.	Digital Subscriber Loop Telephone #:	
6.	PIC (Preferred Long Distance Carrier #):	
7.	Pick-up Group #:	
8.	Call Forward Busy DN:	
9.	CXR Interconnect Dialing:	Allow
10.	ISDN Service:	Lucent Custom
11.	Line Code (U Interface):	2B1Q
12.	Digital Subscriber Loop Service:	Multipoint
13.	Number of Terminals:	2
14.	Associated DN:	
Bearer Service:		
15.	B1 Channel: DMD	16. B2 Channel: None
		17. D Channel: SX
18.	Maximum Number of B Channels:	1
19.	Circuit Switched Channel Options:	CSV-Any
20.	Terminal Configuration Group:	TCS40D
21.	Terminal Type:	D
22.	TKS:	Yes
23.	Display:	Yes
24.	BRCS Features (* optional):	
	* Automatic Call Back Calling	/ACBC
	* Call Forward Variable Feature Button	/CFVFB
	* Directed Call Pickup Non Barge-in, Originate	/CPDNO
	* Call Pickup Terminating	/CPUT
	* Dial Call Waiting	/CWD
	Deluxe Display	/DIDLX
	Distinctive Ringing	/DRIC
	Centrex Group	/IDP
	ICLID & OCLID Displays – All (appearances)	/LIDADAO or /LIRCNMA
	ISDN Conference/Transfer Individual All (calls)	/MWICTIA
	* 6 Party Conference – All Calls	/MWI6WC
	Unrestricted Dialing / Route Dial Errors To Tones	/TGUUT
	* Directed Call Park	/CPDPARK
	* Call Park Answer Back	/CPANSBK
	* ISDN Intercom	/ICM
25.	Call Preference:	Idle
26.	Autohold:	No
27.	One Touch:	No
28.	PDN Call Appearance:	
29.	PDN Call Appearance Quantity:	
Subaddress Definition:		
30.	SAR QTY (Number of CAs to be Reserved):	
31.	SAR ORIG (Reserve CA for originations):	
32.	SAR TERM (Reserve CA for terminations):	
33.	Incoming:	
34.	Intercom:	
35.	ORIG CW:	
36.	PP:	

	Directory Number	CA #	DN Type	CA Qty	Call Exclusion	Ringing Pattern	Deny Termination
37.			Primary		A	Normal	No
38.			Secondary		A	Normal	No
39.			Secondary		A	Normal	No
40.			Secondary		A	Normal	No
41.			Secondary		A	Normal	No

2260d Translation Order Guide #2

Recommended Switch Configuration Group Definition

Configuration Group:	TCS40D
CPE Component:	0
Range:	41
RMK:	Tone Commander 40d or 2260d ISDN Console

Button List:

Button	Feature	Action	Parameter	Description
41				
42				
43				
44				
45				
46				
47				
48				
49				
50				
51	/IC*	[1-4]COM		ISDN Intercom
52	/CPANSBK	ANSBACK		Call Park Answer Back
53	/CPDPARK	DPARK		Directed Call Park
54	/DI*	TODUSE		Time & Date
55	/DI*	INSUSE		Inspect
56	/CWD	CWDLU		Priority Call (Dial Call Waiting)
57	/CFVFB	BNTOG		Call Forwarding On/Off
58	/CPDNO	DPN		Directed Call Pickup w/o Barge-in
59	/CB*	ACBFBP		Auto Callback On/Off
60				
61				
62				
63				
64				

2260d Translation Order Guide #3

Primary Directory Number Configuration – Tone Commander 2260d Console, DSS Keys 1-60

1.	Customer Name:	
2.	Customer Contact:	
3.	Service Address:	
4.	Billing Telephone #:	
5.	Digital Subscriber Loop Telephone #:	
6.	PIC (Preferred Long Distance Carrier #):	N/A
7.	Pick-up Group #:	N/A
8.	Call Forward Busy DN:	N/A
9.	CXR Interconnect Dialing:	N/A
10.	ISDN Service:	Lucent Custom
11.	Line Code (U Interface):	2B1Q
12.	Digital Subscriber Loop Service:	Multipoint
13.	Number of Terminals:	2
14.	Associated DN:	
Bearer Service:		
15.	B1 Channel:	None
16.	B2 Channel:	DMD
17.	D Channel:	SX
18.	Maximum Number of B Channels:	1
19.	Circuit Switched Channel Options:	CSV-Any
20.	Terminal Configuration Group:	None
21.	Terminal Type:	D
22.	TKS:	Yes
23.	Display:	None
24.	BRCS Features:	
	Centrex Group	/IDP
25.	Call Preference:	Idle
26.	Autohold:	No
27.	One Touch:	No
28.	PDN Call Appearance:	61
29.	PDN Call Appearance Quantity:	1
Subaddress Definition:		
30.	SAR QTY (Number of CAs to be Reserved):	None
31.	SAR ORIG (Reserve CA for originations):	None
32.	SAR TERM (Reserve CA for terminations):	None
33.	Incoming:	None
34.	Intercom:	None
35.	ORIG CW:	None
36.	PP:	None

	Directory Number	CA #	DN Type	CA Qty	Call Exclusion	Ringling Pattern	Deny Termination
37.		61	Primary	1	N	Normal	No

Tone Commander 2260d Installation Instructions

Lucent
Custom ISDN

2260d Translation Order Guide #4

Shared Call Appearance Assignments – Tone Commander 2260d Console, DSS Keys 1-30

PDN for DSS keys: _____

DSS Key #	Directory Number	CA #	CA QTY	Manual Exclusion	Ringing Pattern
1		1	1	N	NORMAL
2		2	1	N	NORMAL
3		3	1	N	NORMAL
4		4	1	N	NORMAL
5		5	1	N	NORMAL
6		6	1	N	NORMAL
7		7	1	N	NORMAL
8		8	1	N	NORMAL
9		9	1	N	NORMAL
10		10	1	N	NORMAL
11		11	1	N	NORMAL
12		12	1	N	NORMAL
13		13	1	N	NORMAL
14		14	1	N	NORMAL
15		15	1	N	NORMAL
16		16	1	N	NORMAL
17		17	1	N	NORMAL
18		18	1	N	NORMAL
19		19	1	N	NORMAL
20		20	1	N	NORMAL
21		21	1	N	NORMAL
22		22	1	N	NORMAL
23		23	1	N	NORMAL
24		24	1	N	NORMAL
25		25	1	N	NORMAL
26		26	1	N	NORMAL
27		27	1	N	NORMAL
28		28	1	N	NORMAL
29		29	1	N	NORMAL
30		30	1	N	NORMAL

2260d Translation Order Guide #5

Shared Call Appearance Assignments – Tone Commander 2260d Console, DSS Keys 31-60

PDN for DSS keys: _____

DSS Key #	Directory Number	CA #	CA QTY	Manual Exclusion	Ringing Pattern
31		31	1	N	NORMAL
32		32	1	N	NORMAL
33		33	1	N	NORMAL
34		34	1	N	NORMAL
35		35	1	N	NORMAL
36		36	1	N	NORMAL
37		37	1	N	NORMAL
38		38	1	N	NORMAL
39		39	1	N	NORMAL
40		40	1	N	NORMAL
41		41	1	N	NORMAL
42		42	1	N	NORMAL
43		43	1	N	NORMAL
44		44	1	N	NORMAL
45		45	1	N	NORMAL
46		46	1	N	NORMAL
47		47	1	N	NORMAL
48		48	1	N	NORMAL
49		49	1	N	NORMAL
50		50	1	N	NORMAL
51		51	1	N	NORMAL
52		52	1	N	NORMAL
53		53	1	N	NORMAL
54		54	1	N	NORMAL
55		55	1	N	NORMAL
56		56	1	N	NORMAL
57		57	1	N	NORMAL
58		58	1	N	NORMAL
59		59	1	N	NORMAL
60		60	1	N	NORMAL

Tone Commander 2260d Installation Instructions