



2260d Translation Order Guide #1

Primary Directory Number Configuration – Tone Commander 2260d Console

1.	Customer Name:	
2.	Customer Contact:	
3.	Service Address:	
4.	Billing Telephone #:	
5.	Digital Subscriber Loop Telephone #:	
6.	PIC (Preferred Long Distance Carrier #):	
7.	Pick-up Group #:	
8.	Call Forward Busy DN:	
9.	CXR Interconnect Dialing:	Allow
10.	ISDN Service:	National ISDN
11.	Line Code (U Interface):	2B1Q
12.	Digital Subscriber Loop Service:	Standard
13.	Number of Terminals:	2
14.	Associated DN:	
Bearer Service:		
15.	B1 Channel:	DMD
16.	B2 Channel:	None
17.	D Channel:	SX
18.	Maximum Number of B Channels:	1
19.	Circuit Switched Channel Options:	CSV-Any
20.	Terminal Configuration Group:	TCS40DNI
21.	Terminal Type:	C
22.	EKTS:	CACH
23.	TKS:	Yes
24.	Display:	Yes
25.	BRCS Features (* optional):	
	* Call Forward Variable	/CFIV
	* Directed Call Pickup Non Barge-in, Originate	/CPDNO
	* Call Pickup Terminating	/CPUT
	Distinctive Ringing	/DRIC
	Centrex Group	/IDP
	ICLID & OCLID Displays – All (appearances)	/LIDADAO or /LIRCNMA
	ISDN Conference/Transfer Individual All (calls)	/MWICTIA
	* 6 Party Conference	/MWI6WB2
	Redirecting Number Display	/RND
	Unrestricted Dialing / Route Dial Errors To Tones	/TGUUT
	* Directed Call Park	/CPDPARK
	* Call Park Answer Back	/CPANSBK
26.	Call Preference:	Idle
27.	Autohold:	No
28.	One Touch:	No
29.	PDN Call Appearance:	
30.	PDN Call Appearance Quantity:	

	Directory Number	CA #	DN Type	CA Qty	Call Exclusion	Ringing Pattern	Deny Termination
31.			Primary		A	Normal	
32.			Secondary		A	Normal	
33.			Secondary		A	Normal	
34.			Secondary		A	Normal	
35.			Secondary		A	Normal	


2260d Translation Order Guide #2

Recommended Switch Configuration Group Definition

Configuration Group:	TCS40DNI
CPE Component:	0
Range:	41
RMK:	Tone Commander 40d or 2260d ISDN Console

Button List:

Button	Feature	Action	Parameter	Description
41				
42				
43				
44				
45				
46				
47				
48				
49				
50				
51				
52				
53				
54				
55	/CPANSBK	ANSBACK		Call Park Answer Back
56	/CPDPARK	DPARK		Directed Call Park
57	/CFIV	CFBN		Call Forward Variable
58	/CPDNO	DPN		Directed Call Pickup, Non Barge-in
59				
60	/*	CONF		Conference
61	/*	XFER		Transfer
62	/*	DROP		Drop
63				
64				



2260d Translation Order Guide #3

Primary Directory Number Configuration – Tone Commander 2260d Console, DSS Keys

1.	Customer Name:	
2.	Customer Contact:	
3.	Service Address:	
4.	Billing Telephone #:	
5.	Digital Subscriber Loop Telephone #:	
6.	PIC (Preferred Long Distance Carrier #):	N/A
7.	Pick-up Group #:	N/A
8.	Call Forward Busy DN:	N/A
9.	CXR Interconnect Dialing:	N/A
10.	ISDN Service:	National ISDN
11.	Line Code (U Interface):	2B1Q
12.	Digital Subscriber Loop Service:	Standard
13.	Number of Terminals:	2
14.	Associated DN:	
Bearer Service:		
15.	B1 Channel:	None
16.	B2 Channel:	DMD
17.	D Channel:	SX
18.	Maximum Number of B Channels:	1
19.	Circuit Switched Channel Options:	CSV-Any
20.	Terminal Configuration Group:	None
21.	Terminal Type:	C
22.	EKTS:	CACH
23.	TKS:	Yes
24.	Display:	None
25.	BRCS Features:	
	Centrex Group	/IDP
26.	Call Preference:	Idle
27.	Autohold:	No
28.	One Touch:	No
29.	PDN Call Appearance:	61
30.	PDN Call Appearance Quantity:	1

	Directory Number	CA #	DN Type	CA Qty	Call Exclusion	Ringing Pattern	Deny Termination
31.		61	Primary	1	N	Normal	No

Tone Commander 2260d Installation Instructions

Lucent
National ISDN

2260d Translation Order Guide #4

Shared Call Appearance Assignments – Tone Commander 2260d Console, DSS Keys 1-30

PDN for DSS keys: _____

DSS Key #	Directory Number	CA #	CA QTY	Manual Exclusion	Ringing Pattern
1		1	1	N	NORMAL
2		2	1	N	NORMAL
3		3	1	N	NORMAL
4		4	1	N	NORMAL
5		5	1	N	NORMAL
6		6	1	N	NORMAL
7		7	1	N	NORMAL
8		8	1	N	NORMAL
9		9	1	N	NORMAL
10		10	1	N	NORMAL
11		11	1	N	NORMAL
12		12	1	N	NORMAL
13		13	1	N	NORMAL
14		14	1	N	NORMAL
15		15	1	N	NORMAL
16		16	1	N	NORMAL
17		17	1	N	NORMAL
18		18	1	N	NORMAL
19		19	1	N	NORMAL
20		20	1	N	NORMAL
21		21	1	N	NORMAL
22		22	1	N	NORMAL
23		23	1	N	NORMAL
24		24	1	N	NORMAL
25		25	1	N	NORMAL
26		26	1	N	NORMAL
27		27	1	N	NORMAL
28		28	1	N	NORMAL
29		29	1	N	NORMAL
30		30	1	N	NORMAL

2260d Translation Order Guide #5

Shared Call Appearance Assignments – Tone Commander 2260d Console, DSS Keys 31-60

PDN for DSS keys: _____

DSS Key #	Directory Number	CA #	CA QTY	Manual Exclusion	Ringing Pattern
31		31	1	N	NORMAL
32		32	1	N	NORMAL
33		33	1	N	NORMAL
34		34	1	N	NORMAL
35		35	1	N	NORMAL
36		36	1	N	NORMAL
37		37	1	N	NORMAL
38		38	1	N	NORMAL
39		39	1	N	NORMAL
40		40	1	N	NORMAL
41		41	1	N	NORMAL
42		42	1	N	NORMAL
43		43	1	N	NORMAL
44		44	1	N	NORMAL
45		45	1	N	NORMAL
46		46	1	N	NORMAL
47		47	1	N	NORMAL
48		48	1	N	NORMAL
49		49	1	N	NORMAL
50		50	1	N	NORMAL
51		51	1	N	NORMAL
52		52	1	N	NORMAL
53		53	1	N	NORMAL
54		54	1	N	NORMAL
55		55	1	N	NORMAL
56		56	1	N	NORMAL
57		57	1	N	NORMAL
58		58	1	N	NORMAL
59		59	1	N	NORMAL
60		60	1	N	NORMAL

Tone Commander 2260d Installation Instructions