

40d120 Translation Order Guide #1

Primary Directory Number Configuration – Tone Commander 40d Console

1. Customer Name:	
2. Customer Contact:	
3. Service Address:	
4. Billing Telephone #:	
5. PIC (Preferred Long Distance Carrier #):	
6. SNPA (area code):	
7. Directory Number:	
8. LTCLASS:	BRAFS
Default Logical Terminal:	N
9. EKTS:	Y
CACH:	Y
10. Bearer Service Restrictions:	NOPMD NOCMD
11. CS:	Y
PS:	N
12. Version:	FUNCTIONAL
Issue:	2
13. SPID-Suffix:	01
14. TEI:	DYNAMIC
15. NCOS:	0
RING:	Y
16. Line Class Code:	ISDNKSET
17. MAXKEYS:	64
18. Other Terminal PDN associated with this BRI:	NONE

19. Directory Number Assignments

Key	DN Type	Directory Number	MADN Type	Primary	CA	Ringing	Bridging
1						YES	NO
2						YES	NO
3						YES	NO
4						YES	NO
5						YES	NO
6						YES	NO
7						YES	NO
8						YES	NO
9						YES	NO
10						YES	NO
11						YES	NO
12						YES	NO
13						YES	NO
14						YES	NO

20. Feature Assignments

	Key	Feature	Description
a.	1		Controller
b.			
c.	7	DTM	Deny Termination on MDN
d.	8	DTM	Deny Termination on MDN
e.			
f.	57	CFU N	Call Forward Universal, No Overflow
g.			
h.	60	FC 3	Flexible Calling, 3 party conference
i.	61	Transfer IMP CTALL	Call Transfer, All Call Types
j.	62	DROP	Drop last party from conference

Tone Commander 40d120 Installation Instructions

Nortel
National ISDN-2

40d120 Translation Order Guide #2

Primary Directory Number Configuration – Tone Commander 120d Console, DSS Keys 1-60

1. Customer Name:	
2. Customer Contact:	
3. Service Address:	
4. Billing Telephone #:	
5. PIC (Preferred Long Distance Carrier #):	
6. SNPA (area code):	
7. Directory Number:	
8. LTCLASS:	BRAFS
Default Logical Terminal:	N
9. EKTS:	Y
CACH:	Y
10. Bearer Service Restrictions:	NOPMD NOCMD
11. SLBRI:	N
12. CS:	NI2
PS:	N
13. Version:	FUNCTIONAL
Issue:	2
14. TEI:	DYNAMIC
15. NCOS:	0
RING:	Y
16. Line Class Code:	ISDNKSET
17. MAXKEYS:	64
18. Other Terminal PDN associated with this BRI:	

19. Directory Number Assignments

See 40d120 Translation Order Guide #3 and #4.

20. Feature Assignments

None required.

40d120 Translation Order Guide #3

Shared Call Appearance Assignments – Tone Commander 120d Console, DSS Keys 1-30

PDN for DSS keys 1-60: _____

DSS Key #	Network CA #	DN Type	Directory Number	MADN Type	Primary	Ringing	Bridging
1	1	DN			YES	YES	NO
2	2	MDN		SCA	NO	YES	NO
3	3	MDN		SCA	NO	YES	NO
4	4	MDN		SCA	NO	YES	NO
5	5	MDN		SCA	NO	YES	NO
6	6	MDN		SCA	NO	YES	NO
7	7	MDN		SCA	NO	YES	NO
8	8	MDN		SCA	NO	YES	NO
9	9	MDN		SCA	NO	YES	NO
10	10	MDN		SCA	NO	YES	NO
11	11	MDN		SCA	NO	YES	NO
12	12	MDN		SCA	NO	YES	NO
13	13	MDN		SCA	NO	YES	NO
14	14	MDN		SCA	NO	YES	NO
15	15	MDN		SCA	NO	YES	NO
16	16	MDN		SCA	NO	YES	NO
17	17	MDN		SCA	NO	YES	NO
18	18	MDN		SCA	NO	YES	NO
19	19	MDN		SCA	NO	YES	NO
20	20	MDN		SCA	NO	YES	NO
21	21	MDN		SCA	NO	YES	NO
22	22	MDN		SCA	NO	YES	NO
23	23	MDN		SCA	NO	YES	NO
24	24	MDN		SCA	NO	YES	NO
25	25	MDN		SCA	NO	YES	NO
26	26	MDN		SCA	NO	YES	NO
27	27	MDN		SCA	NO	YES	NO
28	28	MDN		SCA	NO	YES	NO
29	29	MDN		SCA	NO	YES	NO
30	30	MDN		SCA	NO	YES	NO

Tone Commander 40d120 Installation Instructions

Nortel
National ISDN-2

40d120 Translation Order Guide #4

Shared Call Appearance Assignments – Tone Commander 120d Console, DSS Keys 31-60

PDN for DSS keys 1-60: _____

DSS Key #	Network CA #	DN Type	Directory Number	MADN Type	Primary	Ringing	Bridging
31	31	MDN		SCA	NO	YES	NO
32	32	MDN		SCA	NO	YES	NO
33	33	MDN		SCA	NO	YES	NO
34	34	MDN		SCA	NO	YES	NO
35	35	MDN		SCA	NO	YES	NO
36	36	MDN		SCA	NO	YES	NO
37	37	MDN		SCA	NO	YES	NO
38	38	MDN		SCA	NO	YES	NO
39	39	MDN		SCA	NO	YES	NO
40	40	MDN		SCA	NO	YES	NO
41	41	MDN		SCA	NO	YES	NO
42	42	MDN		SCA	NO	YES	NO
43	43	MDN		SCA	NO	YES	NO
44	44	MDN		SCA	NO	YES	NO
45	45	MDN		SCA	NO	YES	NO
46	46	MDN		SCA	NO	YES	NO
47	47	MDN		SCA	NO	YES	NO
48	48	MDN		SCA	NO	YES	NO
49	49	MDN		SCA	NO	YES	NO
50	50	MDN		SCA	NO	YES	NO
51	51	MDN		SCA	NO	YES	NO
52	52	MDN		SCA	NO	YES	NO
53	53	MDN		SCA	NO	YES	NO
54	54	MDN		SCA	NO	YES	NO
55	55	MDN		SCA	NO	YES	NO
56	56	MDN		SCA	NO	YES	NO
57	57	MDN		SCA	NO	YES	NO
58	58	MDN		SCA	NO	YES	NO
59	59	MDN		SCA	NO	YES	NO
60	60	MDN		SCA	NO	YES	NO

40d120 Translation Order Guide #5

Primary Directory Number Configuration – Tone Commander 120d Console, DSS Keys 61-120

1. Customer Name:	
2. Customer Contact:	
3. Service Address:	
4. Billing Telephone #:	
5. PIC (Preferred Long Distance Carrier #):	
6. SNPA (area code):	
7. Directory Number:	
8. LTCLASS:	BRAFS
Default Logical Terminal:	N
9. EKTS:	Y
CACH:	Y
10. Bearer Service Restrictions:	NOPMD NOCMD
11. SLBRI:	N
12. CS:	NI2
PS:	N
13. Version:	FUNCTIONAL
Issue:	2
14. TEI:	DYNAMIC
15. NCOS:	0
RING:	Y
16. Line Class Code:	ISDNKSET
17. MAXKEYS:	64
18. Other Terminal PDN associated with this BRI:	

19. Directory Number Assignments

See 40d120 Translation Order Guide #6 and #7.

20. Feature Assignments

None required.

Tone Commander 40d120 Installation Instructions

Nortel
National ISDN-2

40d120 Translation Order Guide #6

Shared Call Appearance Assignments – Tone Commander 120d Console, DSS Keys 61-90

PDN for DSS keys 61-120: _____

DSS Key #	Network CA #	DN Type	Directory Number	MADN Type	Primary	Ringing	Bridging
61	1	DN			YES	YES	NO
62	2	MDN		SCA	NO	YES	NO
63	3	MDN		SCA	NO	YES	NO
64	4	MDN		SCA	NO	YES	NO
65	5	MDN		SCA	NO	YES	NO
66	6	MDN		SCA	NO	YES	NO
67	7	MDN		SCA	NO	YES	NO
68	8	MDN		SCA	NO	YES	NO
69	9	MDN		SCA	NO	YES	NO
70	10	MDN		SCA	NO	YES	NO
71	11	MDN		SCA	NO	YES	NO
72	12	MDN		SCA	NO	YES	NO
73	13	MDN		SCA	NO	YES	NO
74	14	MDN		SCA	NO	YES	NO
75	15	MDN		SCA	NO	YES	NO
76	16	MDN		SCA	NO	YES	NO
77	17	MDN		SCA	NO	YES	NO
78	18	MDN		SCA	NO	YES	NO
79	19	MDN		SCA	NO	YES	NO
80	20	MDN		SCA	NO	YES	NO
81	21	MDN		SCA	NO	YES	NO
82	22	MDN		SCA	NO	YES	NO
83	23	MDN		SCA	NO	YES	NO
84	24	MDN		SCA	NO	YES	NO
85	25	MDN		SCA	NO	YES	NO
86	26	MDN		SCA	NO	YES	NO
87	27	MDN		SCA	NO	YES	NO
88	28	MDN		SCA	NO	YES	NO
89	29	MDN		SCA	NO	YES	NO
90	30	MDN		SCA	NO	YES	NO



40d120 Translation Order Guide #7

Shared Call Appearance Assignments – Tone Commander 120d Console, DSS Keys 91-120

PDN for DSS keys 61-120: _____

DSS Key #	Network CA #	DN Type	Directory Number	MADN Type	Primary	Ringing	Bridging
91	31	MDN		SCA	NO	YES	NO
92	32	MDN		SCA	NO	YES	NO
93	33	MDN		SCA	NO	YES	NO
94	34	MDN		SCA	NO	YES	NO
95	35	MDN		SCA	NO	YES	NO
96	36	MDN		SCA	NO	YES	NO
97	37	MDN		SCA	NO	YES	NO
98	38	MDN		SCA	NO	YES	NO
99	39	MDN		SCA	NO	YES	NO
100	40	MDN		SCA	NO	YES	NO
101	41	MDN		SCA	NO	YES	NO
102	42	MDN		SCA	NO	YES	NO
103	43	MDN		SCA	NO	YES	NO
104	44	MDN		SCA	NO	YES	NO
105	45	MDN		SCA	NO	YES	NO
106	46	MDN		SCA	NO	YES	NO
107	47	MDN		SCA	NO	YES	NO
108	48	MDN		SCA	NO	YES	NO
109	49	MDN		SCA	NO	YES	NO
110	50	MDN		SCA	NO	YES	NO
111	51	MDN		SCA	NO	YES	NO
112	52	MDN		SCA	NO	YES	NO
113	53	MDN		SCA	NO	YES	NO
114	54	MDN		SCA	NO	YES	NO
115	55	MDN		SCA	NO	YES	NO
116	56	MDN		SCA	NO	YES	NO
117	57	MDN		SCA	NO	YES	NO
118	58	MDN		SCA	NO	YES	NO
119	59	MDN		SCA	NO	YES	NO
120	60	MDN		SCA	NO	YES	NO

Tone Commander 40d120 Installation Instructions